

14.4V6A Lead Acid Battery Charger for 12V SLA / AGM / GEL Batteries

Technical Datasheet

Phonix Charger – Industrial Battery Charger Manufacturer

<https://phonixcharger.com>

Product Overview

This technical datasheet describes the 14.4V6A lead-acid battery charger designed for charging 12V sealed lead acid batteries including SLA, AGM, GEL, VRLA and WET lead-acid batteries. The charger uses a multi-stage charging process (Pre-charge, Constant Current, Constant Voltage and Automatic Cut-off) to ensure safe, stable and efficient battery charging.

Key Features

- Multi-stage charging: Pre-charge, CC, CV and automatic cut-off
- Compatible with SLA, AGM, GEL, VRLA and wet lead-acid batteries
- Wide AC input range 100-240V
- LED charging status indicator
- Multiple protections: OVP, OCP, short circuit and reverse protection
- High efficiency design $\geq 86\%$
- Industrial compact design
- OEM / ODM customization available

Technical Specifications

Parameter	Specification
Brand	Phonix
Model	FX1446000
AC Input	100~240V, 50/60Hz
Input Voltage Range	90~264V
Rated Input Current	1.0A RMS
Max Input Power	95W

DC Output Voltage	14.4V
Output Voltage Range	12V ~ 14.4V
Charging Current	6A $\pm$ 10%
Charging Voltage	14.4V $\pm$ 0.2V
Pre-charge Current	0.5A ($\leq$ 10.8V battery)
Charge End Current	$\leq$ 1A $\pm$ 10%
Output Max Power	87W
Battery Type	12V Lead Acid (SLA / AGM / GEL / VRLA / WET)
Efficiency	$\geq$ 86%
Ripple Voltage	$\leq$ 150mV
Operating Temperature	-10°C ~ +40°C
Storage Temperature	-40°C ~ +70°C
Humidity	0 ~ 95% RH
Cooling	Natural cooling
Size	135*58*36mm
Weight	450 g
Safety Certifications	CE / UL / TUV / FCC / PSE / CCC
MTBF	30000 Hours

Typical Applications

- 12V sealed lead acid battery charging
- Backup power systems
- Security and alarm systems
- Emergency lighting batteries
- Industrial electronic equipment

Manufacturer Information

Manufacturer: Phonix

Whatsapp: +86-19124269133

Email: sales@phonixcharger.com

Product Page:

<https://phonixcharger.com/14-4v-6a-lead-acid-battery-charger-for-12v-sla-agm-gel-battery-packs/>

Official Website: <https://phonixcharger.com>

